



F3



### INSTALLATION

The luminaire will mount to a 3" OD post or tenon with (6) 5/16" black oxide coated stainless steel set screws to ensure a solid connection. The diffuser will be held to the fitter by (4) 5/16 black oxide coated stainless steel captive set screws.

### ELECTRICAL

The easily accessible ballast will be High Power Factor (HPF), core and coil type, pre-wired and tested. The ballast will be removed by loosening two thumb screws and releasing the quick disconnect wiring harness. The glazed white porcelain socket will be medium or mogul base, 4KV pulse rated with a copper alloy nickel plated screw shell and center contact. All components are UL recognized and will be an integral part of the luminaire. The luminaire will carry an ETL label "Suitable for wet location".